



# TeSys Power

## Switch-disconnector fuses

### Product references

NFC Cartridge fuses - Type aM / gG - From 0.25 to 125 A							
Fuse type	Maximum rated voltage	Rating	Sold in lots of	Fuses without striker			
				Unit reference			
	V ~	A		aM	gG		
 DF2CA●●●● DF2CN●●	Cylindrical 8.5 x 31.5	400	1	10	-	DF2BN0100	
			2	10	DF2BA0200	DF2BN0200	
			4	10	DF2BA0400	DF2BN0400	
			6	10	DF2BA0600	DF2BN0600	
			8	10	-	DF2BN0800	
			10	10	-	DF2BN1000	
			12	10	-	DF2BN1200	
			16	10	-	DF2BN1600	
			20	10	-	DF2BN2000	
			 DF2EA●●●● DF2EN●●	Cylindrical 10 x 38	500	0.50	10
1	10	DF2CA01				-	
2	10	DF2CA02				DF2CN02	
4	10	DF2CA04				DF2CN04	
6	10	DF2CA06				DF2CN06	
8	10	DF2CA08				DF2CN08	
10	10	DF2CA10				DF2CN10	
12	10	DF2CA12				DF2CN12	
16	10	DF2CA16				DF2CN16	
20	10	-				DF2CN20	
400	20	10				DF2CA20	-
	25	10				DF2CA25	DF2CN25
	32	10				DF2CA32	DF2CN32
	40	10	-	-			
Cylindrical 14 x 51	690	0.25	10	DF2EA002	-		
		0.50	10	DF2EA005	-		
	500	16	10	DF2EA16	-		
		20	10	DF2EA20	-		
		25	10	DF2EA25	DF2EN25		
		32	10	DF2EA32	DF2EN32		
400	40	10	DF2EA40	DF2EN40			
	50	10	DF2EA50	DF2EN50			
Cylindrical 22 x 58	690	10	10	-	DF2FN10		
		20	10	-	DF2FN20		
		25	10	-	DF2FN25		
		32	10	-	DF2FN32		
		40	10	DF2FA40	DF2FN40		
	500	50	10	DF2FA50	DF2FN50		
		63	10	DF2FA63	DF2FN63		
		80	10	DF2FA80	DF2FN80		
		100	10	DF2FA100	DF2FN100		
		400	125	10	DF2FA125	-	

Switch-disconnector fuses



For protection of equipment with current peaks  
For protection of circuits without significant current peaks